

NEW

220 MHz 50 Watt Mobile JT220M



50 Watts Finally a 220 MHz radio with some power! 50 watts on high, 25 watts on medium, 10 watts on low.

99 Memory Channels Plenty of memory channels to program your favorite repeater/simplex frequencies into.

Large LCD Display A large frequency readout so you can be sure what frequency you are on!

CTCSS Encode and Decode CTCSS tones are built in. Including tone scan. These are also stored in your memory channels.

Full 220 Band Coverage Transmit and receive from 222-224.995 MHz.

Scan Both memory and band scan. You can scan your favorites or look for new ones.

Time Out Timer Timer on the transmitter so you don't time out the repeater

Computer Programmable Free software available online at www.jetstream-usa.com. (Requires optional JTPRG1 cable)

Backlit DTMF Mic The large DTMF buttons on the microphone light up!

1 Year Limited Warranty

800-524-4889

www.jetstream-usa.com

JETSTREAM

**220 MHz
50 Watt Mobile
JT220M**

JETSTREAM

General Specifications

Frequency Range	TX: 222.000-224.995 Mhz RX: 216.000-280.000 MHz
Mode	FM/Narrow FM
Frequency Rate	12.5 kHz
Number of Memory Channels	99 Channels
Antenna Impedance	50 Ohms
Frequency Stability	+/- 5ppm
Microphone Impedance	2k Ohms
Voltage Range	11.7-16 VDC
Current	Transmit: < 9A, Receive: < 600 mA
Working Temperature	14-140 Degrees F
Grounding	Negative
Size	5.7"W X 1.85"H x 7.5"D
Weight	2.7 Lbs

Transmitter Specifications

Output Power	High: 50 Watts Medium: 25 Watts Low: 10 Watt
Modulation	FM
Residual Radiation	-60dB or Below
Max Frequency Deviation	+/- 5KHz, +/- 2.5KHz (Narrow Band Mode)

Receiver Specifications

Receiver Type	Double Conversion
If Frequency	First: 21.7MHz, Second: 450 KHz
Squelch Sensitivity	-16.0 dBu (.1 uV)
Selectivity	>60db/12.5KHz, >70db/25KHz
Intermodulation	>65dB
Audio Power	2.0W (8 ohm, 10% distortion)

Optional Accessories

JTM220BM	Mobile Antenna with Mag Mount
JTMIC1	Replacement DTMF Microphone
JTMB1	Mobile Mounting Bracket
JTPC3	Power Cord
JTPRG1	Programming Cable
JTCIG2	Cigarette Lighter Cable
JTAL1A	Alarm Cable A with wire
JTAL1B	Alarm Cable B, extension
JTPS14B	14 amp power supply for base use

Supplied Accessories

JTMIC1	DTMF Microphone
JTMB1	Mobile Mounting Bracket
JTPC3	Power Cord
JT220MOM	Operating Manual

800-524-4889

www.jetstream-usa.com

*Jetstream
100 Hancock
Hamilton, Ohio 45011
513-868-1353
800-524-4889
513-868-6574 fax*